

DURACELL®

2 AMP BATTERY MAINTAINER 15 AMP BATTERY CHARGER

Portable Power



Rapid Charge Technology delivers faster charging than traditional chargers

Duracell® battery chargers are lightweight, portable and easy to use anytime, anywhere. They are plug-and-play charging solutions that require no installation or setup, and are ideal for extending and recharging all types of 12-volt batteries.

2 Amp Battery Maintainer

Product Features:

- ▶ 2-amp constant DC output current
- ▶ Micro-processor controlled three-stage charging extends battery life
- ▶ Easy battery connection through three types of connectors provided with the unit: clip leads, DC lighter plug and ring terminals
- ▶ "Plug and play" charging solution; requires no installation or setup
- ▶ Wide voltage range operation (90 to 132 V, 50/60 Hz)
- ▶ Small footprint, lightweight and includes detachable mounting feet

Product Applications:

- ▶ Recharge and maintain: motorcycle, ATV, snowmobile, personal watercraft and lawn tractor batteries

15 Amp Battery Charger

Product Features:

- ▶ 15-amp constant DC output current
- ▶ Micro-processor controlled three-stage charging extends battery life
- ▶ Selectable charge rate for all types of 12-volt lead-acid batteries
- ▶ Built-in storage compartment for charger cables
- ▶ Short-circuit and over-charge protection for safe operation

Product Applications:

- ▶ Recharge and maintain: motorcycle, ATV, snowmobile, personal watercraft, lawn tractor, compact car, minivan, SUV, RV and boat batteries (deep cycle)




2 Amp Battery Maintainer



15 Amp Battery Charger

Retail Package



www.duracellpower.com

Duracell® 2 Amp Battery Maintainer

Product Specifications	
AC	
Output current	2 A
Output voltage (nominal):	
Charge	14.4 Vdc
Float	13.0 Vdc
Equalize	n/a
AC input voltage	115 V, 50/60 Hz
Inverter no-load current	N/A
Inverter low-battery shutdown	N/A
DC	
Internal battery type (recommended)	Sealed lead-acid, AGM
Internal battery size (recommended)	6 - 50 Ah
Internal battery voltage	N/A
Charging type	Three stage (see note below)
Charging efficiency	80%

General Specifications	
Part number	804-0027-07
Unit dimensions (L x W x H)	5.5 x 3.2 x 2.5" (14 x 8.3 x 6.4 cm)
Unit weight	1 lb (0.45 kg)
Warranty	Twelve months
Operating temperature	32°F to 104°F (0°C to 40°C)
Storage temperature	77°F to 158°F (-25°C to 70°C)

Packaging Specifications - Duracell® 2 Amp Battery Maintainer

	Retail Package*	Inner Carton	Master Carton
Size (L x W x H)	8.75 x 5.0 x 2.75" (22.2 x 12.7 x 7.0 cm)	N/A	15.0 x 9.5 x 6.0" (38.1 x 24.1 x 15.2 cm)
Count	1	N/A	5
Weight	1.7 lb (0.8 kg)	N/A	9.3 lb (4.2 kg)
UPC number	609525752427	N/A	

* Box

Packaging Specifications - Duracell® 15 Amp Battery Charger

	Retail Package*	Inner Carton	Master Carton
Size (L x W x H)	12 x 6.75 x 8.5" (30.5 x 17.1 x 21.6 cm)	N/A	23.25 x 13.0 x 9.5" (59.1 x 33.0 x 24.1 cm)
Count	1	N/A	4
Weight	5.4 lb (2.4 kg)	N/A	23.3 lb (10.8 kg)
UPC number	609525752342		

* Box


Note: Three-Stage Charging

Multistage charging ensures batteries receive optimum charging, but with minimal wear and tear, regulating the voltage and current delivered to the batteries in three automatic stages:

Bulk: Replaces 70-80% of the battery's state of charge at the fastest possible rate.

Absorption: Replenishes the remaining 20-30% of charge, bringing the battery to a full charge at a slow, safe rate.

Float: Voltage is reduced and held constant in order to prevent damage and keep batteries at a full charge.



Specifications subject to change without notice

Battery-Biz Inc.