

DURACELL®

POCKET INVERTER 100 & 175

Portable Power



Converts Power from your Vehicle to Run and Recharge AC & USB Devices

Duracell® Pocket Inverters 100 & 175 convert 12-volt DC battery power from a vehicle into 120-volt household AC electricity. Each model includes a three-prong household AC outlet and a USB charge port, allowing you to operate and recharge a wide range of mobile devices. When your laptop, Palm®, iPod®, BlackBerry®, or any other mobile device runs out of battery power, simply plug it into one of the Duracell® Pocket Inverters and keep going.

Duracell® Pocket Inverters 100 & 175 are the smallest inverters on the market, and will store easily in your pocket, laptop bag, vehicle console or glove box.

Product Features:

- ▶ Converts 12-volt DC power from your vehicle battery into 120-volt AC electricity
- ▶ Three-prong AC outlet to handle all chargers and adapters for mobile electronics
- ▶ USB charge port
- ▶ Backlit LED On/Off power indicator
- ▶ DC cable with vehicle adapter
- ▶ Over-temperature shutdown
- ▶ Low-battery voltage shutdown (10.5 Vdc and automatic reset)
- ▶ Overload shutdown



Portable power in your vehicle



Retail Package



www.duracellpower.com

Pocket Inverter 100

Product Specifications

AC	
AC output power (max. continuous)	80 W
AC output power (peak)	100 W
AC output surge capacity (peak)	160 W
AC output voltage (nominal)	120 V
AC output frequency	60 Hz
AC output waveform	Modified sine wave
Inverter no-load current	0.5 A
Inverter voltage shutdown	Yes (10.5 Vdc with automatic reset)
USB output power (continuous)	0.5 A

General Specifications

Part number	813-0281-07
Unit dimensions (L x W x H)	3.95 x 2.6 x 9.3" (10 x 6 x 23.6 cm)
Unit weight	0.2 lb (0.09 kg)
Warranty	Twelve months
Operating temperature	32°F to 104°F (0°C to 40°C)
Storage temperature	-4°F to 140°F (-20°C to 60°C)
DC cable with vehicle adapter	Yes

Packaging Specifications - Pocket Inverter 100

	Retail Package*	Inner Carton	Master Carton	Pallet
Size (L x W x H)	6 x 2.5 x 9.9" (15.2 x 6.4 x 25.1 cm)	8 x 6.4 x 10.4" (20.3 x 16.3 x 26.4 cm)	13.5 x 8.75 x 11.25" (34.3 x 22.2 x 28.6 cm)	40 x 48 x 71.5" (101.6 x 121.9 x 71.5 cm)
Count	1	5	10	720
Weight	0.6 lb (0.3 kg)	3.5 lb (1.6 kg)	7.9 lb (3.6 kg)	N/A
Volume	N/A	N/A	1330 cu.in.	N/A
UPC number	609525752229			

* Blister Pack

Packaging Specifications - Pocket Inverter 175

	Retail Package*	Inner Carton	Master Carton	Pallet
Size (L x W x H)	6 x 3 x 9.9" (15.2 x 7.6 x 25.1 cm)	9 x 6.5 x 10.25" (22.9 x 16.5 x 26 cm)	13.75 x 9.9 x 11.25" (34.9 x 25.1 x 28.6 cm)	40 x 48 x 71.25" (101.6 x 121.9 x 18.9 cm)
Count	1	5	10	720
Weight	0.8 lb (0.4 kg)	4.3 lb (1.95 kg)	9.6 lb (4.3 kg)	N/A
Volume	N/A	N/A	1330 cu.in.	N/A
UPC number	609525752236			

* Blister Pack

Specifications subject to change without notice

Pocket Inverter 175

Product Specifications

AC	
AC output power (max. continuous)	130 W
AC output power (peak)	175 W
AC output surge capacity (peak)	260 W
AC output voltage (nominal)	120 V
AC output frequency	60 Hz
AC output waveform	Modified sine wave
Inverter no-load current	0.5 A
Inverter voltage shutdown	Yes (10.5 Vdc with automatic reset)
USB output power (continuous)	0.5 A

General Specifications

Part number	813-0291-07
Unit dimensions (L x W x H)	3.95 x 2.6 x 9.3" (10 x 6 x 23.6 cm)
Unit weight	0.2 lb (0.09 kg)
Warranty	Twelve months
Operating temperature	32°F to 104°F (0°C to 40°C)
Storage temperature	-4°F to 140°F (-20°C to 60°C)
DC cable with vehicle adapter	Yes

